Model : MX9101C



Descriptions :

Chairman of the microphone, delegate microphone, the same shape, compared to delegate microphone, one more priority red button, this button can close all open delegate microphone.

Features :

- Goosenect Condenser mic with LED indicator
- Dual button with Priority Switch
- Noise Cancelling
- Included Cabel cord 2meters
- 8pin parallel connector port output

Specification :

MODEL	MX9101C
Transducer Type	Condenser
Frequency response	40Hz-16000Hz
Output Impedance	200 Ω
Sensitivity	-40dB (± 2dB)
Point	the super-cardioid
Output	balanced / unbalanced output
Record Output	500mV 200Ω
Input Power	AC220V 50Hz
Microphone Cable length	2.1m
Priority Function	Yes (Has a priority button to turn off all delegate microphones)
Usage Limits	No limits (Can be turned on at any time without restriction)

©2025TechmaTechnology-Spesifications are subject to change without prior notice